



SIMPLY BETTER!

### B & K Components, Ltd.

## FUSE LISTING

Current Models	Main AC (Line)	Rail (Internal)	Speaker
ST125.1	8A SB /250V	4A SB / 250V	N/A
Reference 200.1	12A SB / 250V	6A SB / 250V	N/A
ST55.2	8A SB / 250V	4A SB / 250V	N/A
ST125.2	8A SB /250V	4A SB / 250V	N/A
Reference 200.2	12A SB / 250V	6A TL / 250V	N/A
ST125.3	8A SB /250V	4A SB / 250V	N/A
Reference 200.3	12A SB / 250V	6A SB / 250V	N/A
AV2600	8A SB /250V	4A SB / 250V	N/A
AV125.5	12A SB / 250V	4A SB / 250V	N/A
AV125.7	12A SB / 250V	4A SB / 250V	N/A
Reference 200.5	15A SB / 250V	6A SB / 250V	6A SB / 250V
Reference 200.7	15A SB / 250V	6A SB / 250V	6A SB / 250V
AV1260	12A SB / 250V	4A SB / 250V	N/A
AVR 505/507	12A SB / 250V	4A SB / 250V in Surrounds 6A TL in the Mains	N/A
Reference 50	0.5A FB /250V	N/A	N/A
PT5	0.5A FB /250V	N/A	N/A
Phono 10	0.5A FB /250V	N/A	N/A
CT310	12A SB / 250V	N/A	N/A
CT610	12A SB / 250V	N/A	N/A

#### KEY

TL - TIME LAG  
SB - SLOW BLOW  
FB - FAST BLOW  
A - AMPERES  
V - VOLTS



SIMPLY BETTER!

## B & K Components, Ltd.

Current Models	Main AC (Line)	Rail (Internal)	Speaker
<b>ST140M</b>	8A SB /250V	4A SB / 250V	N/A
<b>ST220M</b>	12A SB / 250V	12A SB / 250V	N/A
<b>ST260</b>	8A SB / 250V	4A SB / 250V	N/A
<b>ST2140</b>	8A SB /250V	4A SB / 250V	N/A
<b>Reference 2220</b>	12A SB / 250V	6A TL / 250V	N/A
<b>ST3140</b>	8A SB /250V	4A SB / 250V	N/A
<b>Reference 3220</b>	12A SB / 250V	6A SB / 250V	N/A
<b>AV2600</b>	8A SB /250V	4A SB / 250V	N/A
<b>AV5125</b>	12A SB / 250V	4A SB / 250V	N/A
<b>AV6125</b>	12A SB / 250V	4A SB / 250V	N/A
<b>Reference 7250 II</b>	15A SB / 250V	6A SB / 250V	6A SB / 250V
<b>Reference 7260 II</b>	15A SB / 250V	6A SB / 250V	6A SB / 250V
<b>Reference 7270</b>	15A SB / 250V	6A SB / 250V	6A SB / 250V
<b>AV1260</b>	12A SB / 250V	4A SB / 250V	N/A
<b>AVR 305/307</b>	12A SB / 250V	4A SB / 250V	N/A
<b>Reference 30</b>	0.5A FB /250V	N/A	N/A
<b>PT3 II</b>	0.5A FB /250V	N/A	N/A
<b>Phono 10</b>	0.5A FB /250V	N/A	N/A
<b>CT310</b>	12A SB / 250V	N/A	N/A
<b>CT610</b>	12A SB / 250V	N/A	N/A

### KEY

TL - TIME LAG  
SB - SLOW BLOW  
FB - FAST BLOW  
A - AMPERES  
V - VOLTS



SIMPLY BETTER!

## B & K Components, Ltd.

Models	Main AC (Line)	Rail (Internal)	Speaker
<b>ST 1400M series II</b>	8A SB /250V	4A SB / 250V	N/A
<b>Reference 4420M</b>	12A SB / 250V	12A SB / 250V	N/A
<b>ST1200 series II</b>	8A SB / 250V	4A SB / 250V	N/A
<b>ST1400 series II</b>	8A SB /250V	4A SB / 250V	N/A
<b>ST3030 series II</b>	8A SB / 250V	4A SB / 250V	N/A
<b>Reference 4420</b>	12A SB / 250V	6A TL / 250V	N/A
<b>ST1430 series II</b>	8A SB /250V	4A SB / 250V	N/A
<b>Reference 4430</b>	12A SB / 250V	6A SB / 250V	N/A
<b>AV2500 series II</b>	8A SB / 250V	4A SB / 250V	N/A
<b>AV5000 II</b>	12A SB / 250V	4A SB / 250V	N/A
<b>AV6000 II</b>	12A SB / 250V	4A SB / 250V	N/A
<b>AVR101/202</b>	12A SB / 250V	4A SB / 250V	N/A
<b>Reference 10 / 20</b>	0.5A FB / 250V	N/A	N/A
<b>Reference 7250</b>	15A SB / 250V	6A SB / 250V	6A SB / 250V
<b>Reference 7260</b>	15A SB / 250V	6A SB / 250V	6A SB / 250V
<b>PT3</b>	0.5A FB /250V	N/A	N/A
<b>DT-1</b>	0.5 A FB / 250V	N/A	N/A

### KEY

TL - TIME LAG  
SB - SLOW BLOW  
FB - FAST BLOW  
A - AMPERES  
V - VOLTS



SIMPLY BETTER!

## B & K Components, Ltd.

Models	Main AC (Line)	Rail (Internal)	Speaker
<b>ST 140</b>	8A SB / 250V	4A FB / 250V	4A FB / 250V
<b>ST140M</b>	8A SB / 250V	6A FB / 250V	6A FB / 250V
<b>ST202</b>	8A SB / 250V	6A FB / 250V	6A FB / 250V
<b>ST202+</b>	8A SB / 250V	6A FB / 250V	6A FB / 250V
<b>ST3030</b>	8A SB / 250V	6A FB / 250V	N/A
<b>EX442</b>	12A SB / 250V	6A FB / 250V	6A FB / 250V
<b>EX4420</b>	12A SB / 250V	6A SB / 250V	N/A
<b>M200</b>	12A SB / 250V	6A FB / 250V	6A FB / 250V
<b>EX4420M</b>	12A SB / 250V	6A SB / 250V	N/A
<b>TX4430</b>	12A SB / 250V	6A SB / 250V	N/A
<b>AV2500</b>	8A SB / 250	8A SB / 250V	N/A
<b>PRO600</b>	12A SB / 250V	6A FB / 250V	6A FB / 250V
<b>VIDEO5</b>	12A SB / 250V	4A FB / 250V	N/A
<b>AV654</b>	12A SB / 250V	4A FB / 250V	N/A
<b>ST2020</b>	8A SB / 250V	4A SB / 250V	N/A
<b>PRO5/10</b>	0.5A FB / 250V	N/A	N/A
<b>AVP's</b>	0.5A FB / 250V	N/A	N/A
<b>CS115/117</b>	0.5A FB / 250V	N/A	N/A

### KEY

TL - TIME LAG  
SB - SLOW BLOW  
FB - FAST BLOW  
A - AMPERES  
V - VOLTS